

**Circuit Diagrams for Washable Miniature Switches**

CIRCUIT CODE	SWITCHING FUNCTION			Single Pole
	POS 1	POS 2	POS 3	
	KEYWAY "Y" OPTION			
	STAMPING THIS SIDE			
<b>SINGLE POLE</b>				<b>Double Pole</b>
121	ON	OFF	ON	
123	ON	NONE	ON	
126	ON	NONE	MOM	
127	MOM	OFF	MOM	
131	ON	OFF	MOM	
<b>TERMINAL CONNECTIONS</b>	2 - 3	OPEN	2 - 1	
<b>DOUBLE POLE</b>				<b>SP3T</b>
221	ON	OFF	ON	
223	ON	NONE	ON	
226	ON	NONE	MOM	
227	MOM	OFF	MOM	
231	ON	OFF	MOM	
<b>TERMINAL CONNECTIONS</b>	2 - 3 5 - 6	OPEN	2 - 1 5 - 4	
<b>SP3T</b>				
232	ON	ON	ON	
233	ON	ON	MOM	
235	MOM	ON	MOM	
<b>TERMINAL CONNECTIONS</b>	2 - 3 5 - 6	2 - 3 5 - 4	2 - 1 5 - 4	
<b>Schematics:</b>				
S.P.		D.P.		
STAMPING ON TOP		STAMPING ON OPPOSITE SIDE		
A TERMINALS		AV2 TERMINALS		